

## FLIR CM78 1000A clamp meter with IR thermometer

The FLIR CM78 is a true RMS industrial grade 1000A clamp meter for the electrician who needs a safe, capable combination tool.

- Integrated IR thermometer provides fast non-contact measurements on panels, conduits, and motors
- Powerful worklights not only assist with clamping but are bright enough to serve as a primary worklight
- FLIR Tools Mobile connects the FLIR CM78 to your compatible smartphones and tablets via Bluetooth\*
- METERLiNK® technology wirelessly integrates electrical readings on your infrared image with METERLiNK-enabled FLIR thermal cameras

· Voltage and current, min, max, average, auto power off, data hold, relative, peak hold, battery status indicator, bright white LED backlight

## Includes:

• 6 AAA batteries, user manual/CD, CAT IV silicone test leads and limited lifetime warranty

TECHNICAL SUMMARY	MAX RANGE	BASIC ACCURACY
AC/DC current	1000A	±2.5%
AC/DC voltage	1000V	±1.5%
Resistance	40.00ΜΩ	±1.5%
Capacitance	4.000mF	±3%
Frequency	4000Hz	±1.5%
Temperature (IR)	-20 to 518°F, -20 to 270°C	±2%
IR distance to target ratio	8 inches away : 1 inch spot size	
Type K temperature (optional probe)	-4 to 1400°F, -20 to 760°C	±3%

<sup>\*</sup> See www.flir.com for latest compatibility information and more warranty details





GENERAL INFORMATION		
Bluetooth range max	32ft (10m)	
Jaw opening	1.7in (42mm, 1500MCM)	
Category rating	CAT IV-600V, CAT III-1000V	
Warranty	Limited lifetime*	

## **Ordering Information**

...... 1000A true RMS clamp meter + IR thermometer CM78-NIST...... CM78 with certificate of traceability to NIST TA80......CAT IV silicon test leads



FLIR Commercial Systems Luxemburgstraat 2 2321 Meer Belgium

Tel. : +32 (0) 3665 5100 Fax : +32 (0) 3303 5624 E-mail : flir@flir.com

FLIR Systems France 20, bd de Beaubourg 77183 Croissy-Beaubourg France Tel.: +33 (0)1 60 37 55 02 E-mail: flir@flir.com

Distributed by:





99. rue Beranger 92320 Chatillon - France

Tel: +33 (0)1 71 16 17 00 Fax: +33 (0)1 71 16 17 03 www.testoon.com